

Phone 978-988-9199 • Fax 978-988-0770 www.fishman.com 009-067-001 2-97

340-D Fordham Road Wilmington MA 01887 USA

FISHMAN'

not related to defects in material or workmanship 4. Warranty repairs or replacements will be sent automatically free of charge

you of the repair or replacement cost and wait for your authorization to proceed.

product in its original packaging and a protective carton or mailer 3. FISHMAN TRANSDUCERS' technicians will determine whether the item is covered by warranty or if it instead has been damaged by improper customer installation or other causes

5. If FISHMAN TRANSDUCERS determines the item is not covered by warranty, we will notify

- 2. Enclose a copy of the original Bill of Sale as evidence of the date of purchase, with the
- 1. Call FISHMAN TRANSDUCERS at 978-988-9199 for a Return Authorization Number ("RAN")

To return products to FISHMAN TRANSDUCERS, you must follow these steps...

RETURN POLICY

One (1) Year from the date of purchase. If the unit fails to function properly within the warranty period, free repair and the option of replacement or refund in the event that FISHMAN is unable to make repair are FISHMAN's only obligations. This warranty does not cover any consequential damages or damage to the unit due to misuse, accident, or neglect. FISHMAN retains the right to make such determination on the basis of factory inspection. Products returned to FISHMAN for repair or replacement must be shipped in accordance with the Beturn Policy, as follows. This warranty remains valid only if repairs are performed by FISHMAN. This warranty gives you specific legal rights and you may also have other rights which may vary from state to state

INSTALLATION BY A QUALIFIED PROFESSIONAL REPAIRMAN IS STRONGLY RECOMMENDED. FISHMAN TRANSDUCERS WILL NOT BE RESPONSIBLE FOR ANY DAMAGES THAT MAY RESULT FROM IMPROPER INSTALLATION.

The FISHMAN ACOUSTIC MATRIX PROFESSIONAL is warranted to function for a period of

LIMITED WARRANTY

ACOUSSERVING PROFESSIONAL

cating LED and a PHASE SWITCH. varying body sizes. Other features include a battery function indipreamp will tunction at optimum performance levels in guitars of

HOTIWS TRAMS

intormation. Fishman SMART SWITCH. Call Fishman at 978-986-9665 for more through a single stereo instrument cable), you must first install a electret microphone through the Fishman Blender System (routed If you plan to mix the ACOUSTIC MATRIX with an onboard mini

NOITAJJATZNI OZJI

available from Fishman. guide, "The Finer Points of Piezo Installation" by Ken Parker, is It you are new to under saddle piezo installations, a comprehensive

WARNING

MOITAJJATSNI AB90A9MI OT BUD TNBM -URTENI RUOY OT SEDAMAD YNA ROF EJBIENORSER AB TON STRONGLY RECOMMENDED. FISHMAN TRANSDUCERS WILL SI NAMAIA9A JANOISS390A9 DAIJIJAUD A YA NOITAJJATSNI

poor installation. be responsible for any damages that may occur due to misuse or in ground hum or intermittent signal. Fishman Transducers will not NOTE: Always handle the pickup with care. Mishandling may result

Thank you for your purchase of a FISHMAN product. Please read

INSTALLATION GUIDE

ACOUSTIC

MATRIX

PROFESSIONAL

ACTIVE ACOUSTIC GUITAR SYSTEM

WIDE FORMAT:

.125" (3.2 mm) Width

NARROW FORMAT:

.093" (2.3 mm) Width

WARNING

INSTALLATION BY A QUALIFIED PROFESSIONAL REPAIRMAN IS

STRONGLY RECOMMENDED. FISHMAN TRANSDUCERS WILL

NOT BE RESPONSIBLE FOR ANY DAMAGES THAT MAY RESULT

FISHMAN

FROM IMPROPER INSTALLATION

contact our PRODUCT INFORMATION LINE at 978-9665. these instructions carefully. If you have any questions or problems,

ТНЕ ТКАИSDUCER

known materials. exhibits a sensitivity and dynamic range that tar surpasses an otner sensing material available exclusively from Fishman. This material The ACOUSTIC MATRIX pickup is made with a unique co-polymer

traditional ceramic based transducers); providing superb string balentire saddle rather than small sections of it (as is the case with This continuous strip design allows it to sense the motion of the continuous strips of sensing material that are fully EMI shielded. The ACOUSTIC MATANT transducer is a multi-layer configuration of

.eons

your instrument. the transducer helps preserve the beauty and structural integrity of The incredibly small size and convenient under the saddle design of

ЧМАЗЯЧ ЗНТ

adjust the amount of soundhole resonance or "bottom" so that the on the back of the preamp. This internal trim feature can be used to well as a "set it and torget it" SUB-BASS energy trim control located tures BASS, TREBLE, MIDRANGE and BRILLIAUCE controls as -sei tinu "selite" elitorq-wol zint .metzez JANOISSEROR XIATAM The four-band equalizer / preamp is the brain of the ACOUSTIC

THE 50/50 RULE

For adequate coupling between string, saddle and pickup, we recommend that the saddle slot depth (with pickup installed) should equal no more than 50% of the total height of the saddle.

ADJUSTING FOR TOO DEEP A SADDLE SLOT

If the slot (with pickup installed) measures more than 50% of the total saddle height, the pickup performance will often suffer. To correct for too deep a slot, place a wood shim under the pickup. Determine the proper thickness of the shim by subtracting 1/2 of the total saddle height from the slot depth (with pickup installed). Then, remove an amount of material equal to the thickness of the shim from the bottom of the saddle

A pickup in a Guitar with less than a 20° break angle will often have string balance problems as well as poor tone. For such instruments, an adequate break angle can be realized by "ramping" the string slots or (in extreme cases) raising the saddle height and resetting the neck angle.

when there is a 20° (minimum) break angle across the saddle.

for it to perform optimally. The pickup will "see" an acceptable amount of downbearing pressure

There must be an adequate amount of downbearing pressure on the pickup in order

BREAK ANGLE

PARTS LIST

Star Washers

9/16" lenath

1/2" length

Wire Guides

(5) Slider Knobs

WIDE FORMAT

Width

Height:

Length

Acoustic Matrix Pickup

• 1/4" Stereo Jack, with hardware

• 4-40 Screws (4), 3/16" length, with

• 1/4" Aluminum Hex Standoffs (4),

3/16" Brass Hex Jack Screws (4).

• (3) Adhesive-backed Plastic

· Back Plate with Battery Clip

Preamp Cutout Template

• 4-40 Screws (4), 7/16" length

Slider Beze

Preamp



Custom pickup lengths are available from Fishman. **MECHANICAL FACTORS AFFECTING**

ance may result with string spacings greater than this. DO NOT trim the end of the pickups length as ground hum will occur.

The actual sensing area of the pickup is 2.670" long and can accommodate string spacings of up to 2.500" (63.5 mm). Poor string bal-

NOTE: The overall length of the Matrix pickup is 2.700" (68.58mm).

PICKUP DIMENSIONS

Width:

Height

Length:

TOOLS

· Caliper

Router with 1/8" (3 mm)

for Narrow Format)

Rosin Core Solder

• #1 Phillips Screwdriver

Variable Speed Drill

• 15/32" Spade Bit Drill

• 3/32" Allen Wrench

• 1/2" Open End Wrench

NARROW FORMAT

Sensing Area: 2.670" (67.8 mm)

.09375" (2.4 mm)

.043" (1.1 mm)

2.650" (67.3 mm)

O MORE THAN 50%

Wire Strippers

Center Punch

1/8" Twist Drill

(or .9375" Plunging Cutter

• 400 Grit Sandpaper or Scraper

with 1/4" (6 30 mm) cutter

Soldering Iron (30 watt max)

• Flex Shaft Tool with 1" (25.4 mm)

Diameter Saw Blade or Router

PART I - PREPARATION

COMPENSATED SADDLES

pickup.

OR

the closest string.

3. Drill a .09375" hole.

string balance.

tom of the saddle must be FLAT.

for the Acoustic Matrix Wide Format

Rout a .09375" (2.3 mm) wide

slot for the Acoustic Matrix

Narrow Format pickup.

2.500" (63.5 mm) 2.500" (63.5 mm)

Max. recommended string spacing: Max, recommended string spacing:

We recommend a saddle slot length of at least 2.875" (73mm).

.125" (3.2 mm)

.053" (1.35 mm)

2.650" (67.3 mm)

Sensing Area: 2.670" (67.8 mm)

EXCEPTION: Pickups in guitars with a very steep string break angle (25° or more), will generally perform well, even if the saddle slot depth measures more than 50% of the total saddle height.

We do not recommend compensating the saddle under the "B" string. Doing so may twist the saddle and cause uneven pickup response.

PREPARE THE SADDLE SLOT



2. Be certain that the bottom of the slot is FLAT. Deepen an existing slot only enough to obtain a clean, flat surface.

LOCATE THE WIRE HOLE

1. Locate the center of the wire hole no less than .100" (2.5 mm) from

2. Mark the location where the wire will enter the saddle slot. Center the mark between the walls (width) of the slot.

4. Clear wood chips and foreign materials from the saddle slot. 5. Carefully insert (do not bend) the pickup.



AT LEAST .100" (2.54 mm)



PREPARE THE SADDLE

We recommend synthetic materials such as Micarta or Corian as excellent saddle materials for the Acoustic Matrix. Organic materials such as bone or ivory are not as consistent and may result in poor

1. Prepare a .125" wide saddle (.09375" for Narrow Format) The bot-

2. Remove only enough material from the width of the saddle to provide a sliding fit in the slot. To test the fit, the saddle should slide easily in the slot, but should not fall out when overturned. To maintain your current action, the new saddle must be .053" shorter in height (.043" for Narrow Format pickups) than your current saddle.

PART I - PREPARATION Cont'd.

PREAMP CUT-OUT

For guitars with non-laminated sides, we strongly recommend gluing a thin plywood patch inside the guitar before cutting out the cavity. This will prevent cracking and splintering of the cut-out area during cutting, and provide adequate structural support for the preamp.

- 1. Choose the preamp location on the side of the instrument. Note that the bezel has the ability to conform to most curved surfaces on standard size guitars.
- 2. Tape the enclosed Cutout Template to the desired location. Use the flex shaft tool (with 1/2" blade) or the router (with 1/4" cutter) to make the cut-out.
- 3. Drill the screw mounting holes using the 1/8" drill.



PREPARE THE ENDPIN BLOCK

X-Acto Fine-toothed Saw

• 15/32" Spade Bit Drill

Center Punch

TOOLS

- Masking Tape
- Variable Speed Drill
- 1/8" Twist Drill • 1/2" Open End Wrench

• 3/32" Allen Wrench

The objective of this method is to drill a hole in the endblock, with the endpin in place. You may remove a loose endpin and refasten it in the endblock with cyanoacrylate glue before starting this procedure.

- 1. Apply masking tape around the endblock area to protect the instrument
- 2. Locate an X-Acto saw blade 1/16" away from the body and saw off the endpin
- 3. Centerpunch a guide hole in the center of the trimmed endpin.
- 4. Drill a 1/8" pilot hole through the endblock.
- 5. Line up a 15/32" Spade bit in the pilot hole and begin drilling. Maintain a perpendicular plunge in relation to the instrument. Use steady (but not heavy) pressure, especially as the drill exits inside the guitar.

IMPORTANT: To avoid damage to the instrument, let the drill come to

PART II - INSTALLATION

a complete stop before removing it from the hole.

SOLDER THE WIRE CONNECTIONS

1. Insert the pickup in the saddle slot then strip and tin Ο Ο the wire ends. 2. Solder the "hot" wire from the pickup (inner conductor) to the pad marked "IN" on the preamp circuit board. Solder the "ground" wire from the pickup (shield) to the pad marked "GND" on the preamp circuit board. 3. Strip and tin the wire ends of the preamp output cable. Solder the RED wire to TIP, BATT S the BLACK wire to RING and the ground wire to the SLEEVE of the 1/4" jack. \bigcirc Ο



FASTEN THE JACK IN THE ENDPIN HOLE

Follow this sequence when installing the endpin jack:

- 1 Shielding Cap (optional)
- 2 First Large Hex Nut
- 3 Large Dress Washer

4 - Star Washer



The jack should protrude at least 5/16" and no more than 11/32" outside of the body for proper fit. After fitting the small dress washer and nut over the end of the jack, insert the 3/32" allen wrench through the cross drilled hole on the end of the jack. Tighten the nut with the 1/2" open end wrench while holding the jack in place with the allen wrench. Thread and hand tighten the the strap button.

NOTE: With the strap button in place, the end of the jack should protrude slightly to allow proper plug fit.



MOUNT THE PREAMP

The hardware supplied will accommodate guitars with laminated sides that are between .100" and .175" thick. If your guitar has sides less than .100" thick, the slider knobs will not fit in the bezel properly. To make up the difference, use #4-40 washers to shim the preamp inside the instrument or contact Fishman for longer standoffs.

- **1.** Fasten the 3/16" brass hex screws and the 1/4" hex standoffs to the preamp as shown. Note that the mounting holes on the volume control side of the circuit board are slotted to allow for fitting the preamp to the curved surface of the guitar side.
- 2. Temporarily fit the preamp and bezel together on the guitar, with the standoffs finger tight. Fasten the bezel with the #4-40 1/2" screws to check the standoff alignment. Align the standoffs if necessary. Remove the preamp from the guitar. Tighten the aligned standoffs secure.
- 3. Mount the backplate to the preamp with the 3/16" #4-40 screws. Install the battery and string up the guitar.
- 4. Plug the guitar into an amplifier and set all the slider's tone controls to their center positions. On the back of the preamp, there is a recessed Sub-Bass control which is preset at the factory to full boost. This can be used to roll-off the amount of "bottom end" which can cause feedback (especially in larger dreadnought-style guitars). Turn the trim pot counter clockwise for less bass.
- 5. Re-install the preamp into the guitar. Be sure that the low battery LED lines up with the corresponding hole in the bezel.
- 6. Attach the adhesive backed plastic wire guides to the sides or the kerfing of the instrument.
- 7. Insert a 9 Volt Alkaline battery into the battery clip.

IMPORTANT: Although the supplied battery holder should provide adequate capacity to grip the battery at all times, we strongly recommend removal of the battery when shipping your instrument. FAILURE TO REMOVE BATTERY COULD RESULT IN DAMAGE TO YOUR INSTRUMENT. Fishman will not be held responsible for any such damage as a result of shipping or handling.



OPERATION

The output jack of the Acoustic Matrix Professional System is also the power switch for the battery.

When a cable is first plugged into this jack, the BATT/LOW LED will flash momentarily to indicate that the power is on. When the battery power is low, this light will remain lit.

Be sure to unplug the output jack when not in use

to avoid battery drain.

Adjust the volume of the preamp and your amplifier as desired. Using your ears as a guide, set the PHASE switch for proper phase relationship with the sound source (amps, monitors, etc.). This relationship is most audible at louder volumes and will change from room to room and with your position on stage.

TROUBLESHOOTING

| SYMPTOM: Weak string | |
|---|-----------------|
| PROBLEM | |
| Saddle is too tight/loose in slot | Saddl |
| Bottom of saddle is not flat | |
| Bottom of saddle slot is not flat | |
| Less than adequate downbearing pressure | Observe case |
| | |

| SYMPTOM: Hu | |
|-------------------------|--------|
| PROBLEM | |
| Saddle fit is too tight | Sand o |
| Pickup tube is torn | |



ELONGATED HOLES ALLOW FOR FITTING ASSEMBLY TO CURVATURE OF GUITAR



or strings

SOLUTION

le should have a precise, sliding fit in the slot

Flatten bottom of saddle

Rout out saddle slot

ve the 50/50 rule - In extreme belly up ses, a neck reset may be necessary

SOLUTION

off side of the side of the saddle to provide a sliding fit

Replace the pickup

